

Durst load Bank

LBT-24-120B

Durst mobile switched load bank, offering maximum capacity with ease of use.

Features:

- A true portable high capacity load bank
- Digital meters Volt & Amp (Requires. 240 Vac)
- Banana terminals for connection to Data logger
- Fan cooled
- 100% duty cycle
- Nominal voltage 24 Volts DC
- Nominal Amps Switching 12 Position 0-120A
Switch 3. 6 position of 16 amps each Total 96 Amps DC
Switch 2. 6 position of 4 amps each Total 24 Amps DC
- Reverse polarity warning light
- Internal wiring high temperature silicone
- Dc leads 35mm² Flexible Cable 2 Mtrs long
- Suitable for Aviation, Defence, Solar, UPS system, etc
- Powder coated steel cabinet
- Fully insulated clamp, colour coded
- Designed in Australia for Australian conditions & climate
- Custom Built to your requirements on request
- Models available for other voltages and currents
- Carry version available upon request
- More Load for your \$
- Size W=450mm D=420 H=700 (1020 Including handle)
- Weight 34 Kgs.



Load bank picture indicates case design

Optional Features

- Anderson plugs & Sockets
- Terminals for Amp leads
- Analogue Volt meter with dual sprung movement
- Analogue Amp meter with dual sprung movement
- Pneumatic wheels 250mm Diameter



DURST MOTOR & ELECTRIC INDUSTRIES P/L 189-189B ST JOHNS RD, GLEBE NSW 2037
Ph: 02 9660 1755 Fax: 02 9692 0251 Email: sales@durst.com.au Web: www.durst.com.au

LBT-24-120B.doc